

## COMPRESSION CONNECTORS

Kramer's compression connectors reduce service calls by supplying stronger, more secure and longer lasting connections.

Kramer's compression connectors provide full 360 degree electrical continuity even under punishing conditions. Crafted to withstand 80lb (36.3Kg) of force. The radial design reduces the possibility of an impedance problem and can defeat moisture migration, while the large ferrule surface insures proper RF and digital interface. The connectors don't require soldering.

One compression tool for all connectors.  
Color coded connectors.  
Five connectors soled in package.



### SPECIFICATIONS

#### Connector BNC 1 RGB

CENTER CONDUCTOR: 0.015 - 0.025 inch / 0.381 - 0.635 mm  
DIALECTRIC: 0.065 - 0.078 inch / 1.651 - 1.9812 mm  
OUTER JACKET: 0.095 - 0.160 inch / 2.413 - 4.064 mm

#### Connector BNC 15 RGB

CENTER CONDUCTOR: 0.015 - 0.025 inch / 0.381 - 0.635 mm  
DIALECTRIC: 0.095 - 0.105 inch / 2.413 - 2.667 mm  
OUTER JACKET: 0.145 - 0.160 inch / 3.683 - 4.064 mm

#### Connector BNC RG-59

CENTER CONDUCTOR: 0.0317 - 0.0339 inch / 0.8052 - 0.8611 mm  
DIALECTRIC: 0.144 - 0.157 inch / 3.6576 - 3.9878 mm  
OUTER JACKET: 0.232 - 0.273 inch / 5.8928 - 6.9342 mm

#### Connector BNC RG-6

CENTER CONDUCTOR: 0.0399 - 0.0418 inch / 1.0135 - 1.0617 mm  
DIALECTRIC: 0.180 - 0.193 inch / 4.572 - 4.9022 mm  
OUTER JACKET: 0.265 - 0.305 inch / 6.731 - 7.747 mm

#### Connector FC RG-6

CENTER CONDUCTOR: 0.0399 - 0.0418 inch / 1.0135 - 1.0617 mm  
DIALECTRIC: 0.180 - 0.193 inch / 4.572 - 4.9022 mm  
OUTER JACKET: 0.265 - 0.305 inch / 6.731 - 7.747 mm

#### Connector RCA 1 RGB

CENTER CONDUCTOR: 0.015 - 0.025 inch / 0.381 - 0.635 mm  
DIALECTRIC: 0.065 - 0.078 inch / 1.651 - 1.9812 mm  
OUTER JACKET: 0.095 - 0.160 inch / 2.413 - 4.064 mm

#### Connector RCA 15 RGB

CENTER CONDUCTOR: 0.015 - 0.025 inch / 0.381 - 0.635 mm  
DIALECTRIC: 0.095 - 0.105 inch / 2.413 - 2.667 mm  
OUTER JACKET: 0.145 - 0.160 inch / 3.683 - 4.064 mm

#### Connector RCA RG-59

CENTER CONDUCTOR: 0.0317 - 0.0339 inch / 0.8052 - 0.8611 mm  
DIALECTRIC: 0.144 - 0.157 inch / 3.6576 - 3.9878 mm  
OUTER JACKET: 0.232 - 0.273 inch / 5.8928 - 6.9342 mm

#### Connector RCA RG-6

CENTER CONDUCTOR: 0.0399 - 0.0418 inch / 1.0135 - 1.0617 mm  
DIALECTRIC: 0.180 - 0.193 inch / 4.572 - 4.9022 mm  
OUTER JACKET: 0.265 - 0.305 inch / 6.731 - 7.747 mm

### CONFIGURATIONS

#### MODEL

##### Table Connections

#### CONNECTOR BNC 1 RGB

COLOR CODE: ORANGE  
USE FOR: BNC Termination for mini coax cable 26-28 AWG: BC-2X, BCP-2X, BC-5X, BCP-5X, BC-5X5S, BC-3X2T7S, BCP-5X5S

#### CONNECTOR BNC 15 RGB

COLOR CODE: PURPLE  
USE FOR: BNC Termination for mini coax cable 22 AWG

#### CONNECTOR BNC RG-59

COLOR CODE: RED  
USE FOR: BNC Termination for RG-59 coax cable: BC-1X59

#### CONNECTOR BNC RG-6

COLOR CODE: GREEN  
USE FOR: BNC Termination for RG-6 coax cable: BC-1X

#### Connector FC RG-6

COLOR CODE: GREEN  
USE FOR: "f" connector for RG-6 coax cable: BC-1X

#### CONNECTOR RCA 1 RGB

COLOR CODE: ORANGE  
USE FOR: RCA Termination for mini coax cable 2686 AWG: BC-2X, BCP-2X, BC-5X, BCP-5X, BC-5X5S, BC-3X2T7S, BCP-5X5S

#### CONNECTOR RCA 15 RGB

COLOR CODE: PURPLE  
USE FOR: RCA Termination for mini coax cable 22 AWG

#### CONNECTOR RCA RG-59

COLOR CODE: RED  
USE FOR: RCA Termination for RG-59 coax cable: BC-1X59

#### CONNECTOR RCA RG-6

COLOR CODE: GREEN  
USE FOR: RCA Termination for RG-6 coax cable: BC-1X