



KRAMER

FC-331

3G HDSDI to HDMI Format Converter

| HDMI | 3G HD-SDI - BNC



The FC331 is a highperformance format converter for video signals up to 3G HDSDI (Level A). It converts the input video format (with embedded audio) to an HDMI output signal. The FC331MD is certified for medical applications

FEATURES

Multi-Standard Operation - SDI (SMPTE 259M and SMPTE 344M), HDSDI (SMPTE 292M) and 3G HDSDI (SMPTE 424M)

SDI Level A Support

Certified for Medical Applications - According to IEC 6060112 (Electromagnetic Compatibility), (FC331MD)

Looping Input with Reclocking

HDTV Compatible

Audio Group De-embedded Selection

Active Input & Output LED Indicators



KRAMER

TECHNICAL SPECIFICATIONS

INPUT:	1 SD/HD/3G HDSDI (Level A) with loop on BNC connectors
OUTPUTS:	1 HDMI connector
MAX. DATA RATE:	Up to 3Gbps
STANDARD COMPLIANCE:	HDMI
INDICATOR LEDS:	SD/HD, OUT, ON
POWER CONSUMPTION:	5V DC, 400mA
INCLUDED ACCESSORIES:	Power supply
OPTIONS:	RK3T 19" rack adapter
PRODUCT DIMENSION:	12.00cm x 7.15cm x 2.44cm (4.72" x 2.81" x 0.96") W, D, H
PRODUCT WEIGHT:	0.2kg (0.4lbs) approx
SHIPPING DIMENSION:	23.20cm x 12.00cm x 8.90cm (9.13" x 4.72" x 3.50") W, D, H
SHIPPING WEIGHT:	0.5kg (1.1lbs) approx



KRAMER

CONFIGURATIONS

FC-331-MD

3G HDSDI to HDMI Format Converter for Medical Applications

